

# XP SERIES

## COMMERCIAL / CONTRACTOR / RESIDENTIAL PORTABLE GENERATORS

### FEATURES:

- True Power™ brushless alternator - Less than 5% total harmonic distortion
- Generac OHVI® Overhead Valve Industrial Engine With Full Pressure Lubrication and Spin-on Oil Filter
- Steel fuel tank with incorporated fuel gauge
- Mobility kit with locking fold-down handles and never-flat wheels
- 1-1/4" diameter hardened steel tube cradle with corner impact wraps
- All engine controls located on control panel
- Hour meter with maintenance resets
- Covered outlets
- Circuit breaker protected outlets
- Electric start including starting battery
- Low-tone muffler
- 20 foot, 30 amp cord set
- Maintenance Kit

### XP6500E

Model 05605

Running Watts: 6500

Starting Watts: 8125



Ratings	
AC Rated Output	6.5kW / 6500 Watts
AC Maximum Output	8.125 kW / 8125 Watts
AC Voltage	120V/240V
AC Frequency	60 Hz
120 VAC Amperage	Rated 54.1/Starting 67.7
240 VAC Amperage	Rated 27.0/Starting 33.8
Engine	
Engine Type and Displacement	OHVI Single Cylinder 410cc
Oil Capacity w/ Filter Change	1.5 Qt. (1.4 liter)
Oil Capacity w/o Filter Change	1.2 Qt. (1.14 liter)
Low Oil Pressure Shutdown	Standard

Fuel	
Fuel Capacity	9.0 Gallons (34.07 liters)
Run Time @ ½ Load	12.4 Hours
Assembled Dimensions and Weight	
Dimensions L x W x H (inches)	35.5 x 26 x 29
Dimensions L x W x H (mm)	825.5 x 660.4 x 736.6
Unit Weight	230 lbs. (104.3 kg.)
Warranty	
Residential	3 Year Limited
Commercial	2 Year Limited

Outlets

GFCI 4 x 5-20R



1 x L14-30R



Maximum wattage and current are subject to, and limited by, such factors as fuel Btu content, ambient temperatures, altitude, engine condition, etc. Maximum power decreases about 3.5% for each 1,000 feet above sea level; and will also decrease about 1% for each 6° C (10° F) above 16° C (60° F) ambient temperature.